

## **Highlights**

#### Fast Mobile Broadband for All Your Devices

Connect your high-speed mobile broadband connection to multiple Wi-Fi devices such as smartphones, tablets, PCs, and more.

#### Status at a Glance

The OLED display tells you the status of your connection at a glance. See how many devices are connected to conserve data.

#### Go Anywhere

The DWR-932 is small enough to fit in your pocket, and its rechargeable battery means you're not tied to a wall outlet.



## **DWR-932**

# 4G/LTE Mobile Router

#### **Features**

#### Connectivity

- Uses a SIM card to connect to the Internet
- Compatible with 802.11n/g/b wireless devices
- Micro-USB port for easy charging

#### **Portability**

- Up to five hours of battery in one charge so you stay connected longer
- Small size lets you drop it in a purse or pocket and take it wherever you go
- OLED display gives you current status at a glance

#### Security

- Industry Standard WPA/WPA2 Wi-Fi security protocol
- Built-in firewall
- Wi-Fi Protected Setup (WPS) for one-touch setup

The DWR-932 4G/LTE Mobile Router is a 4G/LTE Cat4 high speed broadband wireless WAN (WWAN) to Wi-Fi mobile hotspot. The DWR-932 uses a 4G Internet connection to give you an easy-to-deploy Wi-Fi network anywhere you need one. Instead of limiting your mobile Internet connection to a single device through a USB dongle, the DWR-932 allows you to create a Wi-Fi hotspot to share your connection. The convenient size means you can share your connection anywhere; use it in a cafe to send e-mail while your friend reads the news, or at the airport so you and your coworkers can work while waiting for your plane.

## **Connect Anywhere**

Simply insert your data-enabled SIM card to set up your very own mobile Wi-Fi network. The DWR-932 is perfect for when you need to quickly set up an impromptu network. It's ideal for business trips when you need to share an Internet connection with everybody during a meeting, or use it for travel, allowing you to provide all your travel companions with Internet access.

#### Easy to Set Up

Sharing your Internet connection doesn't have to be a complicated process - just open a web browser to access D-Link's modern, user-friendly graphical web interface. The setup wizard's easy to use step-by-step instructions will have your network up and running in minutes. Implement WPA/WPA2 wireless encryption in minutes with the wireless network setup wizard, or use Wi-Fi Protected Setup (WPS), which establishes a connection to new devices with the touch of a button.

### Flexible Usage

The DWR-932 4G/LTE Mobile Router gives you instant connectivity, all in a powerful yet portable device, that fits easily into your pocket. The rechargeable 2000 mAh Li-ion battery allows you to stay connected for long periods of time, and it's plug-and-play with no complicated software to install. Getting online with the DWR-932 is quick, easy, and convenient.



## **Front View**



Technical Specifications			
General			
Frequency Support <sup>1</sup>	<ul> <li>Cat4 LTE bands 1/3/5/7/8/20/38/40</li> <li>UMTS/HSPA+/DC-HSPA+: 900/2100 MHz</li> </ul>	• GSM/GPRS/EDGE: 850/900/1800/1900 MHz	
Data Throughput <sup>2</sup>	LTE up to 150 Mbps down/50 Mbps up     DC-HSPA+ up to 42 Mbps Up/5.76 Mbps Down	• EDGE up to 236.8 Kbps	
Security	WPA/WPA2 PSK Auto (TKIP/AES)	WPS Push-Button Connection	
Advanced Functions	Built-in firewall     Built-in NAT	• UPnP	
Wi-Fi Data Rates <sup>2</sup>	Up to 300 Mbps with 802.11n clients     6/9/11/12/18/24/36/48/54 Mbps in 802.11g mode	• 1/2/5.5/11 Mbps in 802.11b mode	
Functionality			
Wireless Security Features	WPA/WPA2 PSK Auto (TKIP/AES)	WPS Push-Button connection	
Firewall	Network Address Translation (NAT)		
Advanced Features	L2TP/PPTP/IPSec VPN passthrough DMZ (Demilitarized Zone) Port/Application Forwarding Universal Plug And Play (UPnP)	<ul><li> IP filter</li><li> SMS messaging</li><li> USSD support</li><li> MicroSD mass storage over USB</li></ul>	
Physical			
Interfaces	802.11n/g/b wireless LAN     Standard Mini-SIM/USIM card slot	MicroSD card slot     Micro-USB port	
Antenna	• 2 x internal cellular antennas (1T2R)	• 2 x internal Wi-Fi antennas	

## **DWR-932 4G/LTE Mobile Router**

Display	OLED Display Network type Signal strength Roaming status SMS & SMS status	<ul> <li>Internet connection status</li> <li>Carrier</li> <li>Battery status</li> <li>Wi-Fi &amp; security status</li> <li>Wi-Fi clients</li> </ul>
Power	• DC 5 V/1 A ± 5%	Rechargeable 2000 mAh Li-ion battery
Dimensions	• 105 x 65 x 16 mm (4.13 x 2.55 x 0.59 in)	
Weight	• 100 g (0.22 lb)	
Operating Temperature	• 0 to 40 °C (32 to 104 °F)	
Storage Temperature	• -20 to 70 °C (-4 to 158 °F)	
Operating Humidity	• 10% to 90% (non-condensing)	
Certifications	• CE	• RoHS
Order Information		
Part Number	Description	
DWR-932	4G/LTE Mobile Router	



Supported frequency band is dependent upon regional hardware version.
 Data rates are theoretical. Data transfer rate depends on network capacity and signal strength.
 Updated 2018/03/21