

Phaser® 5550 A3 Black-and-White Laser Printer



		5550N
Speed		Up to 50ppm/ipm (A4)
Duty Cycle		Up to 300,000 pages / month
Paper Handling	Paper input	Tray 1 (MPT): 100 sheets; Custom sizes: 89 x 98mm – 297 x 432mm
		Tray 2: 500 sheets; Custom sizes: 140 x 182mm – 297 x 432mm
		Tray 3: 500 sheets; Custom sizes: 140 x 182mm – 297 x 432mm
	Optional	Tray 4 – 5: 1,000-sheet Feeder; Custom sizes: 140 x 182mm – 297 x 432mm
		Tray 6: 2,000-sheet Feeder; Size: A4
	Envelope Tray: Custom sizes: 98 x 148mm – 162 x 241mm	
Paper output	Standard	500 sheets
	Optional	Stacker: 3,000-sheet Stacker with 500-sheet Top Tray
		Finisher: 3,000-sheet Stacker with 500-sheet Top Tray, 50-sheet multi-position stapling and 3 or 2 / 4 hole-punch
Automatic two-sided printing		Optional
Print		
First-page-out-time		As fast as 6.5 seconds
Resolution (max)		True 1,200 x 1,200dpi
Processor		500MHz
Memory (std / max)		256MB / 1GB
Connectivity		10 / 100 / 1000 Base-T Ethernet, USB 2.0, Parallel
Page description languages		Adobe® Postscript® 3™, PCL®6 / PCL®5e emulation, Direct PDF (with optional Hard Drive)
Print features	Standard	Smart Trays, Booklet printing, Edge-to-edge printing, Negative image, Mirror image, Scaling, Watermarks, Auto fit, Custom-size pages, Covers, Separation pages, RAM collation, N-up, Job completion notification
	Optional	Remote printing, Job accounting
	Optional	Productivity kit (includes 40GB Hard Drive) enables Secure / Proof / Personal / Saved print, Hard disk collation, Print with, PDF-direct printing, Extended font / Form storage
Warranty		Please check with your Fuji Xerox Printers reseller for more information

Device Management*

CentreWare® IS Embedded Web Server, CentreWare® Web, Xerox NDPS Gateway, Xerox Usage Analysis Tool, MailInx email alerts, PrintingScout® Alert Notification, PhaserSMART®

Print Drivers

Windows® 2000 / XP / 2003® Server, Vista, Mac OS® X (10.3 or higher), Novell® Netware® 5.x / 6.5 (NDPS only), Linux® Red Hat®, Fedora™ Core 5, SUSE® 10.0, Unix: Sun Microsystems Solaris™ 9 / 10, IBM AIX® 5.1, HP-UX 11.0 / 11i, Xerox Walk-Up® Printer Drivers with Windows® 2000 or higher

Font Capability

139 Postscript® fonts; 83 PCL® fonts

Media Handling

Trays 1, 3 – 6: 60gsm – 215gsm; Two-sided output: 60gsm – 163gsm; Tray 2: 60gsm – 105gsm; Media types: Plain paper, envelopes, labels, transparencies, card stock

Operating Environment

Temperature: 5°C – 30°C
Humidity: 15% – 85%
Sound pressure: Printing: 54dB(A), Standby: 22dB(A)
Sound power: Printing: 7.19B, Standby: 5.0B
Warm-up time (from power save): As fast as 37 seconds
FPOT from power save: 45 seconds

Electrical

Power: 220VAC – 240VAC, 50 / 60Hz
Power consumption: Printing: 900W, Standby: 105W, Power save: 11W

Dimension (W x D x H)

5550N: 640 x 525 x 498mm
Weight: 41kg

Certifications

Listed to UL 60950-1 / CSA 60950-1-03, 1st Edition, FDA / CDRH – Class 1 Laser Product, FCC Part 15, Class A, Canada ICES-0003, Class A, CE marked, Low Voltage Directive 2006 / 95 / EC, EN 60950-1, 1st Edition, EN 60825-1 – Class 1 Laser Product, EMC Directive 2004 / 108 / EC, EN 55022, Class A, EN 55024, RoHS Directive 2002 / 95 / EC, WEEE Directive 2002 / 96 / EC

What Comes In The Box

- Phaser 5550 Printer
- Toner Cartridge (35,000 print capacity)
- Drum Cartridge (60,000 print capacity)
- World kit (includes Software and documentation CD)

Supplies

Toner Cartridge: 35,000 pages¹ 113R00684
Drum Cartridge: 60,000 pages¹ 113R00685
Staple Pack (15,000) 008R12941


Routine Maintenance Items

Maintenance Kit, 220V: 300,000 pages² 109R00732

Options

Productivity Kit (includes 40GB Hard Drive) 097S03878
Duplex Module 097S03220
1,000-sheet Feeder 097S03716
2,000-sheet Feeder 097S03717
3,500-sheet Stacker with Job Offset 097S03719
3,500-sheet Finisher 097S03282
Envelope Tray 097S03286
256MB Phaser Memory 097S03743
512MB Phaser Memory 097S03635
32MB Flash Memory 097S03880

Phaser®
5550
A3
black-and-white
laser printer



Phaser® 5550 Laser Printer Pure printing power



¹ Average standard pages. Declared Yield in accordance with ISO / IEC 19752. Yield will vary based on image, area coverage and print mode.
² Approximate pages. Declared Yield based on an average job size of 3 pages letter / A4 size. Yield will vary based on job run length, media size and orientation.

Copyright © 2008 Xerox Corporation. All rights reserved. Contents of this publication may not be reproduced in any form without permission of Xerox Corporation. XEROX®, CentreWare®, Phaser®, PhaserSMART®, PrintingScout® and Sphere of Connectivity design are registered trademarks of Xerox Corporation in the U.S. and / or other countries. ENERGY STAR® is a U.S. registered mark. As an ENERGY STAR® partner, Xerox Corporation has determined that this product meets the ENERGY STAR® guidelines for energy efficiency (5550DN / DT). All other trademarks are the property of their respective manufacturers. Product information in this brochure is subject to change without notice. 06/08

For more information, please call
(65) 6351 0118 or visit us at
www.fxprinters.com

Phaser® 5550 Laser Printer

Print more, print faster. Productive, reliable and packed with value, the Fuji Xerox Phaser 5550 laser printer means serious business for any office with diverse and high-volume print demands.

Powerful productivity

Get up to speed with the Phaser 5550 — the A3 laser printer that delivers the ultimate combination of peak performance and impressive print quality.



- **Fast printing at up to 50ppm/ipm** — for both single-sided and two-sided printing respectively — quickly handles even the most demanding print workloads.
- **1,200 x 1,200dpi** print resolution and Fuji Xerox exclusive EA-HG toner technology deliver exceptional print quality without slowing down the printer's outstanding performance.
- **Complex print jobs made easy** — even multi-page jobs with graphics, images and charts — thanks to a powerful 500MHz processor.
- **A first-page-out time as fast as 6.5 seconds** means no waiting, even on a busy network.
- **Custom media sizes plus advanced printing features**, like collation, booklet making and edge-to-edge printing, meet your complex printing needs. Add a finisher for stapling and hole punching.

Smart, reliable operation

The Phaser 5550 laser printer comes loaded with cutting-edge intelligence features that simplify installation and everyday use. And with highly durable components throughout, count on total reliability day after productive day.

- **Easily output heavy print volumes** thanks to a robust duty cycle of 300,000 pages per month.
- **Xerox Installer** automatically installs and configures your printer for easy network connection, getting you up and running in minutes.
- **Private data stays secure** thanks to built-in support for 802.1x and IPv6, the latest network security protocols.
- **Network printing is easier than ever to manage.** Helpful features like CentreWare IS internal web server allow users to manage the device from their computers, and Email Alerts notify administrators of common occurrences, such as low toner levels, before they impact productivity.
- **PhaserSMART® online troubleshooting** provides 24/7 access to the online Xerox Knowledge Base, delivering fast solutions for you to complete work quickly. Plus, PrintingScout® notification delivers instant pop-up messages right to your desktop if print issues arise.

Value throughout

It's simple: The Phaser 5550 laser printer delivers more for your money than any other printer in its class. Its always-low operating costs keep it truly bottom-line friendly.

- **An unbeatable total cost of ownership** results from the printer's affordable purchase price and low cost-per-page.
- **Long-lasting consumables** increase uptime, and separate print drum and toner cartridge allow for optimised use of each component.
- **Expect consistent, trouble-free performance** from a printer that is rated to deliver an impressive 500,000 mean prints between failure.
- **Get best-in-class value** with extensive printer management tools, up to 1GB memory, Adobe® PostScript® 3™, and more.
- **The Usage Analysis Tool and Job Accounting feature** allow you to collect, organise and analyse usage data for tighter cost control.

Extensive paper handling and finishing capabilities

Multiple input and output options for high-volume printing. Print on the widest range of media — from postcard to A3 size, from 60gsm paper to 215gsm card stock, cover, envelopes, labels and transparencies.

Usage tracking simplified

Great for managing budgets, the CentreWare IS internal web server's helpful accounting features make it fast and easy to track device usage and plan ahead for upcoming supply needs.



Paper input

- 1 100-sheet Tray 1 (multipurpose tray) for specialty print jobs
- 2 Optional automatic two-sided printing module
- 3 Two 500-sheet Trays (adjustable to A3)
- 4 Optional 1,000-sheet Feeder provides two additional A3 trays
- 5 Optional 2,000-sheet Feeder (A4) (requires 1,000-sheet Feeder installed)
- 6 Optional Envelope Tray (not shown)

Connectivity

- 7 10/100/1000 Base-T Ethernet for network connectivity
- 8 Optional Productivity Kit (includes 40GB Hard Drive) provides more print features

Paper output


- 9 500-sheet Face-down Output Tray
- 10 Optional 3,500-sheet Finisher for staple / hole punch (3,500-sheet Stacker also available)



Phaser® 5550 Quick Facts

- Print up to 50ppm
- True 1,200 x 1,200dpi
- Powerful 500MHz processor
- Robust 300,000 pages / month duty cycle
- 256MB memory, expandable to 1GB
- First page out time of 6.5 seconds

Print
297 x 432mm
50 ppm
5550N
W x D x H
640 x 525 x 498mm



Phaser 5550N with optional 1,000-sheet Feeder



Phaser® 5550N and accessories

Phaser® 5550N Standard Configuration <ul style="list-style-type: none"> • 3-Tray 1100-sheet capacity • USB and parallel connectivity • 10/100/1000 Base-T Ethernet 	Standard Configuration + Duplex Module	Standard Configuration + Duplex Module + 1,000-sheet Feeder (2,100-sheet total capacity)	Other Options <ul style="list-style-type: none"> • Duplex unit • Productivity Kit (includes 40GB Hard Drive) • 1,000 and 2,000-sheet Feeders • 3,500-sheet Stacker • 3,500-sheet Finisher for staple / hole punch • Envelope Tray
--	---	---	--